
Non-Isolated DC/DC Converter Specification

Model No.: SDJ-72S1205

Version No. 1.0

Input voltage	Output voltage	Output current	Output power	Efficiency	Size
18-90V DC	12V DC	5 Amps	60 Watts	90.6%	64*57*22mm



The SDJ-72S1205 is a Non-isolated DC-DC converter that uses a synchronous rectification technology, and features high efficiency and power density. It has the dimensions of 64mm x 57mm x 22mm (2.52 in. x 2.24 in. x 0.87 in) and provides the rated output voltage of 12V and the maximum output current of 5A.

Features

- Design meeting RoHS / CE
- High efficiency: 90.6% (@ 72Vin, 25℃)
- Non-isolated between input and output
- Small size, high reliability
- Support -40 °C environment
- 100% full load burn-in test
- Short circuit, Over load, Low-voltage protections
- Waterproof level IP67
- 2 Years warranty

Applications

- Industrial
- Alternative Energy
- Golf Cart
- Cars & Forklift
- Electromotor
- Telecommunications
- Boat & Yacht
- Medical
- LED Marketplaces and so on.

Model naming method

SDJ-72S1205

SDJ: Step down type

72 : Input rated voltage

S : Single output type

12 : Output voltage

05 : Output current

Electrical Specifications

Conditions: TA = 25 °C (77°F), Airflow = 1 m/s (200LFM), Vin =72V, Vout =12V, unless otherwise specified.

Parameter	Min.	Typ.	Max.	Units	Remarks
Absolute maximum ratings					
Operating ambient temperature	-40	-	+55	°C	
Shell ambient temperature	-40	-	80	°C	
Storage temperature	-55	-	100	°C	
Operating humidity	5	-	95	%	Non-condensing
Atmospheric pressure	62	-	106	Kpa	
Altitude	-	-	4000	m	
Cooling way	-	-	-		Natural cooling
Input characteristics					
Input voltage	18	72	90	V	-
Max. input voltage	-	-	90	V	Continuous
Undervoltage shutdown	14.7	15.1	15.4	V	Automatic recovery
Undervoltage recovery	16.5	16.7	16.9	V	Automatic recovery
Max. input current	-	-	3.6	A	Vin =18V; Iout =5A
No load current	-	35	50	mA	Vin =72V
Positive electrode cable	18	-	-	AWG	If the wire length is greater than 50cm, it is recommended to use a thicker wire diameter.
Negative electrode cable	18	-	-	AWG	
Enable PIN cable	-	NA	-	AWG	If the unit with this function
Fuse	-	20	-	A	Input positive has built-in fuse
Output characteristics					
Efficiency	-	90.6	-	%	Vin =72V; Iout =5A
Output voltage	11.9	12	12.3	V	Vin =72V; Iout =5A
Regulator accuracy	-	±2	-	%	
Voltage regulation	-	±2	-	%	
Load Regulation	-	±2	-	%	
Overvoltage protection	-	NA	-	V	
Output current	0	-	5	A	Vin=18-90V
Overcurrent protection	-	11	12	A	Vin=72V
External capacitance	-	NA	-	μF	DON'T NEED
Output ripple and noise	-	96	200	mVp-p	Vin =18-90V; Iout=5A Oscilloscope bandwidth: 20 MHz;
Output voltage rise time	-	75	100	mS	
Boot delay time	-	102	120	mS	
Out voltage overshoot	-	1	2	%	Vin =72V
Over temperature protection	-	-	100	°C	Shell test
Short circuit protection	-	YES	-		Long-term (4 hours) short circuit is not damaged, Hiccup mode
Positive electrode cable	18	-	-	AWG	If the wire length is greater than 50cm, it is recommended to use a thicker wire diameter.
Negative electrode cable	18	-	-	AWG	

Safety and EMC features				
Anti-electric Strength	Input to Output	-	V	Leakage current ≤ 3.5mA, 1min, no breakdown, no arcing
	Input to Shell	≥500	V	
	Output to Shell	≥500	V	
Insulation resistance	Input to Output	≥10	MΩ	Test voltage = 500V
	Input to Shell			
	Output to Shell			
Other characteristics				
Weight	≤ 120		g	
Package	white box			
MTBF	≥200,000		H	Vin= 72V; Iout= 5A
Switching frequency	140±10		KHz	

Characteristic Curves

Conditions: TA = 25°C (77°F), Vin = 72V, Vout = 12V, unless otherwise specified.

Figure 1, Efficiency




Figure 2, Power dissipation





Figure 3, Input V-I, Iout=5A



Typical Waveforms

Conditions: TA = 25° C (77° F), Vin = 72V, unless otherwise specified.

Figure 4, 25% - 50% load dynamic




Figure 5, 50% - 75% load dynamic




Figure 6, Output voltage established (Iout = 5A)




Figure 7, Output ripple & noise (Iout = 5A)




Figure 8, Boot delay time





Figure 9, Short circuit & Output voltage




Feature Description


Remote On/Off (EN) (Optional)

Logic Enable	Low level (0 - 18Vdc)	High level (18-90Vdc)	Left open
Positive logic	Off	On	Off

Various circuits for driving the EN



Simple control



Transistor control

Input Undervoltage Protection

The converter will shut down after the input voltage drops below the under-voltage protection threshold for shutdown. The converter will start to work again after the input voltage reaches the input under voltage protection threshold for startup. For the Hysteresis, see the Protection characteristics.

Output Overcurrent Protection

The converter equipped with current limiting circuitry can provide protection from an output overload or short circuit condition. If the output current exceeds the output overcurrent protection set point, the converter enters hiccup mode. When the fault condition is removed, the converter will automatically restart.

Overtemperature Protection

A temperature sensor on the converter senses the average temperature of the module. It protects the converter from being damaged at high temperatures. When the temperature exceeds the over temperature protection threshold, the output will shut down. It will allow the converter to turn on again when the temperature of the sensed location falls by the value of Over temperature Protection Hysteresis


Wiring Instructions

The input and output of this product is terminals. The user should ensure that the input and output wires and terminals are connected reliably, and pay attention to the wire diameter to meet the requirements of the power supply current. If the cable to be used is long, it needs Considering the voltage drop of the wire, if the voltage drop is too large, the voltage output at the load end may not meet the load demand. In this case, consider using a thicker wire diameter or reducing the length of the wire. Generally, if long wiring is required. Long line should be used on the side where the current is relatively small. For example, this product is a step-down product, so long lines should be used on the input side.

Thermal Consideration

Sufficient airflow should be provided to help ensure reliable operating of the SDJ-72S1205.

Therefore, thermal components are mounted on the top surface of the SDJ-72S1205 to dissipate heat to the surrounding environment by conduction, convection, and radiation. Proper airflow can be verified by measuring the temperature at the middle of the base plate.



Dimension

